

	<h1>Technical Bulletin</h1>	<b>Flying Pig Systems</b>	<b>Page 1/2</b>
	<h2>Road Hog 3 Bios Settings</h2>	<b>Rev. Date 23-Nov-09</b>	<b>Rev A</b>

This document contains instructions for configuring the bios settings for your Road Hog 3 console. You can identify the motherboard model of your Road Hog during boot-up or by contacting support.

## Accessing the Bios

- 1) Attach a keyboard to the console and power on the console.
- 2) During the boot process, press and hold the DELETE key
- 3) The BIOS Setup Utility will open.
- 4) Follow the guidelines below to restore the default Road Hog settings per motherboard model.

## (AIMB-562)

The following changes need to be made to each section of the BIOS in the Road Hog computer when using an AIMB-562 motherboard. After making the changes, press F10 to save the configuration and exit.

### MAIN

- > Adjust System time and date
- > Legacy Diskette A: Disabled

### ADVANCED

#### **Chipset**

- > Graphics Adapter Priority: PCI Express/Int-VGA

#### **Onboard Devices Configuration**

- > HD Audio Controller: Enabled
- > Onboard PCIEX GbE LAN: Disabled
- > Serial Port1 Address: Disabled
- > Serial Port2 Address: Disabled
- > Parallel Port Address: Disabled

### POWER

- > ACPI 2.0 Support: Yes

#### **APM Configuration**

- > Restore on AC Power Loss: Power On

#### **Hardware Monitor**

- > CPU Fan
- Profile Mode: Silent Mode

### BOOT

#### **Boot Device Priority**

- > 1st boot: Hard Drive
- > 2nd boot: Removable Device
- > 3rd boot: USB CD-ROM

#### **Boot Settings Configuration**

- > Quick boot: Enabled
- > Full Screen Logo: Disabled
- > Wait for 'F1' if error: Disabled



# Technical Bulletin

Flying Pig  
Systems

Page  
2/2

## Road Hog 3 Bios Settings

Rev. Date  
23-Nov-09

Rev  
A

### (ASUS P5B)

The following changes need to be made to each section of the BIOS in the Road Hog 3 computer when using an Asus P5B motherboard. After making the changes, press F10 to save the configuration and exit.

#### MAIN

- > Adjust System time and date
- > Legacy Diskette A: Disabled

#### ADVANCED

##### **Chipset**

##### **Northbridge Configuration**

- > Initiate Graphics Adapter: PCI/IGD

##### **Onboard Devices Configuration**

- > HD Audio Controller: Enabled
- > Onboard 1394 Controller: Disabled
- > Onboard PCIE GbE LAN: Disabled
- > JMicron SATA/PATA Controller: Enabled
- > Serial Port1 Address: Disabled
- > Parallel Port Address: Disabled

#### POWER

- > ACPI 2.0 Support: Enabled

##### **APM Configuration**

- > Restore on AC Power Loss: Power On
- > Power On By PCI Devices: Disabled
- > Power on By PCIE Devices: Disabled
- > Power on By PS/2 Keyboard: Disabled

##### **Hardware Monitor**

- > Fan Profile: Silent

#### BOOT

##### **Boot Device Priority**

- > 1st boot: CD-ROM
- > 2nd boot: Hard Drive

##### **Boot Settings Configuration**

- > Quick boot: Enabled
- > Full Screen Logo: Enabled
- > Wait for 'F1' if error: Disabled